



RANCILIO KRYO 65 ST / KRYO 65 AT

STANDARD / AUTOMATIC DOSING GRINDERS



DOSING GRINDER SPECIFICATIONS

The KRYO 65 is designed to withstand the daily rigors of any cafe. It features patented cooling grinder chamber which reduces heat from friction during grinding. The KRYO 65 are dosing grinders characterized by innovative technologies and perfect ergonomics, combined with great personality and style.

The KRYO 65 ST grinder continuously grinds coffee beans from the bean hopper when switched on. The KRYO 65 AT grinder has an active doser that automatically turns the grinder off when the dosing chamber is filled. The dosing system of the KRYO 65 can be easily programmed to a range of settings to fit the precise specifications of the user. It has a Micrometric Adjustment knob with lock which ensures to deliver consistent and precise particle size. The ground coffee is then dispensed into a high quality and shock-proof dosing container. The porta-filter holder centers the porta-filter when dosing ground coffee.

MICROMETRIC ADJUSTMENT KNOB



DOSING GRINDER STANDARD FEATURES

- Dosing grinder with chamber for ground coffee for fast and easy distribution
- Adjustable dose lever between 5.5 - 10 grams
- Doser lever is made from aluminum with a SoftGrip finish
- Ergonomic doser lever can be installed on the right or left side
- Patented cooling chamber
- ThermoSteel treated steel 64mm burrs
- Continuous micrometric adjustment knob
- Made from durable die-cast aluminum, ABS and durable food-grade polycarbonate
- Bean hopper holds 2.9 lbs of coffee beans
- Removable hopper with lock
- Comes in Standard (ST) and Automatic (AT) versions in Anthracite Grey
- 1-year parts warranty

DOSING GRINDER STANDARD ACCESSORIES

- Removable Bean hopper with lock
- Removable tray for easy cleaning
- User manual

DOSING GRINDER DATA SPECIFICATIONS

- Weight: 29 lbs
- Power Supply: 110V
- Power Rating: 450 W

COUNTERTOP REQUIREMENTS

Height: 30"	Depth: 18"
Width: 12"	Weight: 29 lbs

SHIPPING DIMENSIONS AND WEIGHT

Height: 23"	Length: 18"
Width: 12"	Weight: 29 lbs

SPACE REQUIREMENTS

Allow 1.5" of clearance on all sides of the machine
Allow space to fill bean hoppers from the top

SERVICE CONNECTIONS

ELECTRICAL CONNECTIONS:

Grinder

Voltage: 110 V


Watts: 450

Circuit Size: 15 Amps

Suggested Receptacle: 5-15R

Power can be installed under or above counter.

Suggested Receptacle
for Dosing Grinder



5-15R